

Operations

BR-D40E

COMPONENT DIGITAL
4:2:2

6

LCD display section



DISPLAY

- 1 OPERATE ON/WARNING indicator
- 2 DA1/DA2 (audio channel 1/audio channel 2) level meter
- 3 AUTO OFF indicator
- 4 DEW indicator
- 5 DIAG indicator
- 6 SERVO UNLOCK indicator
- 7 RF LOW LEVEL indicator
- 8 Lithium backup battery indicator
- 9 MENU indicator
- 10 SLAVE LOCK indicator
- 11 TC PB indicator
- 12 HOLD indicator
- 13 Counter display
- 14 H (hour meter) indicator
- 15 Tape, cassette indicator
- 16 Tape remaining time indicator
- 17 Tape direction indicator
- 18 Battery indicator

CONTROL

- 1 LIGHT
- 2 COUNTER
- 3 COUNTER RESET
- 4 AUDIO LEVEL control DA1/DA2
- 5 AUDIO MONITOR switch
- 6 AUDIO INPUT 1 select switches
- 7 TC GENERATOR PRESET/REGEN switch
- 8 TC GENERATOR REC/FREE RUN switch
- 9 TC DISP TC/SUB TC switch
- 10 AUDIO INPUT LEVEL selection switch
- 11 AUDIO INPUT 2 select switches
- 12 HOLD (GROUP) button
- 13 SHIFT (ITEM) button
- 14 ADVANCE (select) button
- 15 PRESET (DATA SET) button
- 16 ALARM volume
- 17 MENU button

Interface panel



Rear panel



- 1 DC INPUT
- 2 DC OUT
- 3 AUDIO INPUT CH-1/CH-2
- 4 REMOTE/SERVICE connector
- 5 TALLY lamp/switch
- 6 +48 V phantom power switch
- 7 Earphone jack

Left front panel



- 1 AUDIO MONITOR control

Right front panel



- 1 VIDEO OUT
- 2 TC IN
- 3 TC OUT
- 4 AUDIO OUT CH1/CH2



Operation panel section

- 1 EJECT button/Lamp
- 2 REW button/Lamp
- 3 FF button/Lamp
- 4 STOP button/Lamp
- 5 PLAY button/Lamp
- 6 Operation panel cover